

# Tap Position Indicator : EE-601G



**EE-601G**

EMCO Electronics Tap Position Indicator Type EE-601G is used to indicate the tap position of the Power Transformer. 5 digit Gray code along with Common as marked on the rear panel A1 (LSB) to A5 (MSB for Gray code type) is connected to the input of TPI. The corresponding tap no. is indicated on the display.

## Features

- ❖ Microcontroller based architecture
- ❖ Small size, saves space on panel
- ❖ 5 digit Gray Code Input with Common
- ❖ Bright and clear 7-segment displays
- ❖ 95 to 260 V AC/DC Universal Power Supply

## Technical Specifications

Max. No. of tap positions	: 21
Display	: 7 segment LED
Auxiliary Supply	: 95-260V AC/DC, 5VA
Overall Dimensions	: 48 x 96 x 132 mm (H x W x D).
Panel Cutout Dimensions	: 46 x 92 mm (H x W).
Depth	: 110 mm
Operating temperature	: 0°C - 45° C
Weight	: 0.5 Kg. approx.

Product specifications are subject to change without notice.

## EMCO ELECTRONICS

- Mumbai Office** : 302, Vasan Udyog Bhavan, Senapati Bapat Marg, Opp. Phoenix Mill, Lower Parel (W), Mumbai 400013. Tel.: +91-22-2490 2283, 2491 4638. Fax : +91-22-2495 1024. [Email : office@emcoelectronics.org](mailto:office@emcoelectronics.org)
- Factory** : Unit No. 13, Kedarnath Tungareshwar Industrial Complex No. 1, Satalivali, Vasai (E), Dist. Palghar - 401 208. Tel.: +91-250-648 1782 / 1801 / 0114. Fax : +91-250-248 1087  
[Email : mumbai@emcoelectronics.org](mailto:mumbai@emcoelectronics.org), [sales.emcoelectronics@gmail.com](mailto:sales.emcoelectronics@gmail.com)
- Bangalore Office** : 15, Wood Street, (1st Floor) Richmond Road, Bangalore - 560 025  
Tel.: +91-80-2557 0215. Telefax : +91-80-25 666 06  
[Email : emcoblr@emcoelectronics.org](mailto:emcoblr@emcoelectronics.org), [emcosalesbangalore@gmail.com](mailto:emcosalesbangalore@gmail.com)



(An ISO 9001:2015 Co.)

